

Name `list-connector-work-security-maps`– lists the work security maps belonging to the specified resource adapter

Synopsis `list-connector-work-security-maps [--help] [--securitymap securitymap] resource_adapter_name`

Description The `list-connector-work-security-maps` subcommand lists the work security maps belonging to the specified resource adapter.

This subcommand is supported in remote mode only.

Options `--help`

`-?`

Displays the help text for the subcommand.

`--securitymap`

Specifies the name of the security map contained within the resource adapter from which the identity and principals should be listed.

Operands `resource_adapter_name`

The name of the resource adapter for which you want to list security maps.

Examples **EXAMPLE 1** Listing Connector Work Security Maps

This example lists the current connector work security maps for the resource adapter named `my_resource_adapter`.

```
asadmin list-connector-work-security-maps my_resource_adapter
workSecurityMap1: EIS principal=eis-principal-2, mapped principal=server-principal-2
workSecurityMap1: EIS principal=eis-principal-1, mapped principal=server-principal-1
workSecurityMap2: EIS principal=eis-principal-2, mapped principal=server-principal-2
workSecurityMap2: EIS principal=eis-principal-1, mapped principal=server-principal-1
Command list-connector-work-security-maps executed successfully.
```

Exit Status 0 subcommand executed successfully
1 error in executing the subcommand

See Also `create-connector-work-security-map(1)`, `delete-connector-work-security-map(1)`, `update-connector-work-security-map(1)`

asadmin(1M)